



# **Product Instructions**

## **Powerhead For Stainless Manifold (24V)**

#### **Applications**

The Powerhead 15 061 is a two position actuator for zone control which mounts on the return valve of the Stainless Manifold. A 24 V signal actuates the head to open the valve. The position of the valve is normally closed.

The Powerhead may be used on both 1-1/4" Stainless Shut Off/Balancing and Stainless Shut Off/ Balancing/Flow Meter Manifolds. These Powerheads will not fit 1" Brass Manifolds.

#### **Features**

- White in color, Viega logo on front
- Normally closed
- Water resistant
- · All around function indicator
- 360° installation position
- Snap-on installation
- Valve adapter concept
- Initially-Open function
- 3.2 ft. connecting wire

### **Specifications**

Voltage: 24V

Max Inrush Current: 250 mA for 2 minutes maximum

Operating Current: 75 mA

Closing/Opening Time: Approximately 3 minutes


Stroke: 4 mm

Actuating Force: 21lbs.

Weight: 3.5 oz.

Fluid Temperature: 32°F - 212°F






#### Installation

Remove plastic cap from return valve.

- 1. Thread on valve adapter hand tight. Do not use wrench or pliers.
- 2. Once valve adapter is screwed on, simply snap the powerhead on to the valve adapter.



### **ON/OFF Indicator**

The Powerhead for the Stainless Manifold has a cylinder on the top that will raise and expose blue when the valve is open. You will be unable to see any blue when the valve is in its normal closed position.

#### **Initially-Open Function**

The Powerhead is delivered in the open position. This allows for easier installations and also allows for the installer to pressure and flow test each circuit before connecting the

This function is disengaged automatically after the first 6 minutes of powered use.


VIEGA • One Company... One Partner... Delivering System Solutions.





# **Product Instructions**

## **Powerhead For Stainless Manifold (24V)**



VIEGA • One Company... One Partner... Delivering System Solutions.